

Model No: BSE1210-INT

Description: 12 Volt 1.0Amp 2 Stage automatic switchmode SLA battery charger / maintainer with interchangeable input plug Australian version. (Optional input plugs for other regions available separately).

	Product Features:	
	1	2 step charging method; constant current, constant voltage charge
	2	Switching mode power supply (SMPS) technology
	3	Ideal for charging and maintaining all types of 12V lead acid batteries between 3.4Ah to 20Ah
	4	Models available (terminations): BSE1210-INT-A: Alligator clips BSE1210-INT-C: Cigarette lighter plug BSE1210-INT-S: 6.35mm spade terminals
	5	Interchangeable input plugs (BP-11-xx) xx = SA/EU/UK/UL *SA = Australia (INCLUDED); EU = Europe; UK = United Kingdom; UL = USA.
	6	LED charge status indicators
	7	Automatic shut off
	8	Reverse polarity protection
	9	Spark proof design
10	Constar connection	

Terminations: Charger features Constar plug for connection to leads with alligator clips, cigarette plug, spade terminals.

General Specification

AC Input rating:	100 - 240VAC 50/60Hz 20W
DC output rating:	12VDC @ 1.0 Amp
Constant voltage charge:	Adjust the charge current as according to the rise of battery voltage, when the battery voltage rises the output current will be reduced.
Charge complete:	Automatically stop when battery is fully charged at 14.4V.
LED indications:	1. No LED when charge is not commenced, 2. Red LED is glowed when charge is started 3. LED changes to Green color when charge is completed
Operating temperature:	- 20°C ~ 50°C
Charger dimensions:	70mm x 48mm x 37mm
Charger weight:	140g

Packing and shipping details

Clamshell dimensions:	235mm x 168mm x 85mm
Net weight per unit :	~250g
Units per carton:	12
Carton dimensions:	483mm x 388mm x 190mm
Net weight per carton :	3.7kg
Certifications:	CE, GS, SAA, PSE and ETL Approval + RoHS

