

# Phoenix Inverters

180VA – 1200VA 230V/50Hz and 110V/60Hz

[www.victronenergy.com](http://www.victronenergy.com)



**Phoenix Inverter 12/180**

### SinusMax – Superior engineering

Developed for professional duty, the Phoenix range of inverters is suitable for the widest range of applications. The design criteria have been to produce a true sine wave inverter with optimized efficiency but without compromise in performance. Employing hybrid HF technology, the result is a top quality product with compact dimensions, light in weight and capable of supplying power, problem-free, to any load.

### Extra start-up power

A unique feature of the SinusMax technology is very high start-up power. Conventional high frequency technology does not offer such extreme performance. Phoenix Inverters, however, are well suited to power up difficult loads such as computers and low power electric tools.

### To transfer the load to another AC source: the automatic transfer switch

For our lower power models we recommend the use of our Filax Automatic Transfer Switch. The Filax features a very short switchover time (less than 20 milliseconds) so that computers and other electronic equipment will continue to operate without disruption.



**Phoenix Inverter 12/800 with Schuko socket**

### LED diagnosis

Please see manual for a description.

### Remote on/off switch

Connector for remote on/off switch available on all models.

### DIP switch for 50/60Hz selection (48/350 model only)

### Available with different output sockets


Please see pictures below.



**Phoenix Inverter 12/350 with IEC-320 sockets**



**Phoenix Inverter 12/180 with Schuko socket**



**Phoenix Inverter 12/180 with Nema 5-15R sockets**



**Phoenix Inverter 12/800 with IEC-320 socket**



**Phoenix Inverter 12/800 with Schuko socket**



**Phoenix Inverter 12/800 with BS 1363 socket**



**Phoenix Inverter 12/800 with AN/NZS 3112 socket**



**Phoenix Inverter 12/800 with Nema 5-15R socket**

Phoenix Inverter	12 Volt 24 Volt 48 Volt	12/180 24/180	12/350 24/350 48/350	12/800 24/800 48/800	12/1200 24/1200 48/1200
Cont. AC power at 25°C (VA) (3)		180	350	800	1200
Cont. power at 25°C / 40°C (W)		175 / 150	300 / 250	700 / 650	1000 / 900
Peak power (W)		350	700	1600	2400
Output AC voltage / frequency (4)		110 VAC or 230 VAC +/- 3% 50 Hz or 60 Hz +/- 0,1%			
Input voltage range (V DC)		10,5 - 15,5 / 21,0 - 31,0 / 42,0 - 62,0		9,2 - 17,3 / 18,4 - 34,0 / 36,8 - 68,0	
Low battery alarm (V DC)		11,0 / 22 / 44		10,9 / 21,8 / 43,6	
Low battery shut down (V DC)		10,5 / 21 / 42		9,2 / 18,4 / 36,8	
Low battery auto recovery (V DC)		12,5 / 25 / 50		12,5 / 25 / 50	
Max. efficiency (%)		87 / 88	89 / 89 / 90	91 / 93 / 94	92 / 94 / 94
Zero load power (W)		2,6 / 3,8	3,1 / 5,0 / 6,0	6 / 5 / 4	6 / 5 / 6
Zero load power in search mode		n. a.	n. a.	2	2
Protection (2)		a - e			
Operating temperature range		-40 to +50°C (fan assisted cooling)			
Humidity (non-condensing)		max 95%			

#### ENCLOSURE

Material & Colour	aluminium (blue Ral 5012)			
Battery-connection	1)	1)	1)	1)
Standard AC outlets	230V: IEC-320 (IEC-320 plug included), CEE 7/4 (Schuko) 120V: Nema 5-15R			
Other outlets (at request)	BS 1363 (United Kingdom) AN/NZS 3112 (Australia, New Zealand)			
Protection category	IP 20			
Weight (kg / lbs)	2,7 / 5,4	3,5 / 7,7	6,5 / 14,3	8,5 / 18,7
Dimensions (hwxwd in mm) (hwxwd in inches)	72x132x200 2.8x5.2x7.9	72x155x237 2.8x6.1x9.3	104 x 194 x 305 4.1 x 7.6 x 12.0	104 x 194 x 305 4.1 x 7.6 x 12.0

#### ACCESSORIES

Remote on-off switch	Two pole connector			
Automatic transfer switch	Filax			

#### STANDARDS

Safety	EN 60335-1			
Emission Immunity	EN 55014-1 / EN 55014-2 / EN 61000-6-2 / EN 61000-6-3			

- 1) Battery cables of 1.5 meter (12/180 with cigarette plug)
- 2) Protection key:
  - a) output short circuit
  - b) overload
  - c) battery voltage too high
  - d) battery voltage too low
  - e) temperature too high

- 3) Non-linear load, crest factor 3:1
- 4) Frequency can be set by DIP switch (48/350 model only)



#### Battery Alarm

An excessively high or low battery voltage is indicated by an audible and visual alarm, and a relay for remote signalling.



#### BMV-700 Battery Monitor

The BMV-700 Battery Monitor features an advanced microprocessor control system combined with high resolution measuring systems for battery voltage and charge/discharge current. Besides this, the software includes complex calculation algorithms to exactly determine the state of charge of the battery. The BMV-700 selectively displays battery voltage, current, consumed Ah or time to go. The monitor also stores a host of data regarding performance and use of the battery.