

Project information	
Company	
Name	
Subname	
Date	
Executed by	

		Requirements / Criteria	Value	OK	NOK	Notes
<b>Battery installation</b>						
Model						
Serialnumbers						
Firmware version		Latest release				
Clearances	Top	>200mm				
	Right side	>10mm				
	Left side	>10mm				
	Front	>50mm				
	Rear	>50mm				
Ventilation		To be free				
Location	Separate battery room?		Yes / No			
	Room ventiation present?		Yes / No			
	External heat sources next to the batteries?		Yes / No			
Fixation		To be stable	Fixation type: Bracket / Strap / Other:			
Fire extinguishing system			Type:			
Battery configuration	Series					
	Parallel					
Connection configuration	Parallel groups					
Maximum current possible						
Cable diameter used						
Cable lengths of parallel batteries		Lengths must be even.				

Project information	
Company Name	
Subname	
Date	
Executed by	

		Requirements / Criteria	Value	OK	NOK	Notes
<b>MG Master LV installation</b>						
Model						
Serialnumber						
Firmware version		Latest release				
Mounting position		Vertical / Horizontal				
System voltage			24V / 48V			
Fuses	Battery		Voltage: Rating:			
	Power output 1		Voltage: Rating:			Connected to:
	Power output 2		Voltage: Rating:			Connected to:
	Power output 3		Voltage: Rating:			Connected to:
	Power output 4		Voltage: Rating:			Connected to:
VE.CAN Device instance						
DC distributors installed						

<b>Cable check: Power</b>						
Check torque	battery poles	Need to be tight. Max. 15Nm				
	Master LV connections	Need to be tight. Max. 15Nm				
Check connectivity	Battery series and parallel	Conforming schematics				
	Chargers/Loads					

Project information	
Company	
Name	
Subname	
Date	
Executed by	

		Requirements / Criteria	Value	OK	NOK	Notes
<b>Cable check: Communication</b>						
BMS-CAN check	All batteries connected?		Yes / No			
	Terminators present?		Yes / No			
AUX-CAN check	Used?		Yes / No			
	Connected to CCGX?		Yes / No			
	Interface is working?					
Allow-to-charge		Needed to control chargers	Yes / No			Interfaced to:
Allow-to-discharge		Needed to control loads	Yes / No			Interfaced to:

<b>Start-up</b>						
Measure battery voltage						
Configure parallel and series to a fixed number						
Allow-to-charge		Function properly				
Allow-to-discharge		Function properly				
Reset Tracking values						
Reset Events						
Check date/time of Master						Check start-up event time
Charge batteries to synchronize SOC						

Project information	
Company	
Name	
Subname	
Date	
Executed by	

		Requirements / Criteria	Value	OK	NOK	Notes
<b>Charger/Inverter</b>						
Model	Victron Multi 5 kVA					
Serialnumber						
Firmware version		Latest release				
Parallel configuration			Parallel:			Save configuration to PC
	Configured Master/Slave?		Yes / No			
Allow-to-charge	Connected?	Mandatory	Yes / No			AUX.
Allow-to-discharge	Connected?	Mandatory	Yes / No			Temp. Sens
Configure assistants		Lynx Ion BMS				Save assistant to PC

<b>Monitoring devices</b>						
Model	Victron Color Control GX					
Serialnumber						
Firmware version		Latest release				
Check devices	Master LV (Lynx Ion BMS)	Data on display				
	Multi 1	Data on display				
	Multi 2	Data on display				
	Multi 3	Data on display				
	Multi 4	Data on display				