INSTRUCTION MANUAL **RRC2130**



Picture only for reference

Deutsch	Bedienungsanleitung	2
English	Instruction manual	3
Български	Ръководство за употреба	4
Česky	Návod k obsluze	5
中国	使用说明书	6
中國	使用說明書	7
Dansk	Betjeningsvejledning	8
Español	Manual de empleo	9
Français	Manuel d'utilisation	10
□□□□□	ऑपरेटिंग मैन्युअल	11
Italiano	Istruzioni d'uso	12
日本人	取扱説明書	13
한국	사용설명서	14
Latviski	Lietošanas instrukcija	15
Lietuviškai	Naudojimo instrukcija	16
Magyar	Használati utasítás	17
Nederlands	Gebruiksaanwijzing	18
Norsk	Bruksanvisning	19
Português	Manual de instruções	20
Polski	Instrukcja obsługi	21
Română	Instrucţiuni de utilizare	22
Русский	Руководство по эксплуатации	23
Slovenský	Návod na obsluhu	24
Slovensko	Navodila za uporabo	25
Suomi	Käyttöohje	26
Svenska	Bruksanvisning	27
ภาษาไทย	คู่มือแนะนำการใช้งาน	28

Talk to our engineers +61 2 9519 1200 · info@mibattery.com.au · mibattery.com.au

English Instruction manual

This manual contains instructions for use and important safety information. Read the instructions carefully before using the product.

Safety:

- Do not open or dismantle batteries.
- Do not expose batteries to heat or fire. Avoid storage in direct sunlight.
- Do not short-circuit a battery.
- Do not store batteries haphazardly in a box or drawer where they may short-circuit each other or be short-circuited by other metal objects.
- Do not remove a battery from its original packaging until required for use.
- Do not subject batteries to mechanical shock.
- In the event of a battery leaking, do not allow the liquid to come in contact with the skin or eyes. If contact has been made, wash the affected area with copious amounts of water and seek medical advice.
- Do not use any charger other than that specifically provided for use with the equipment. See also chapter "Charging".
- Observe the plus (+) and minus (–) marks on battery and equipment and ensure correct use.
- Do not mix batteries of different manufacture, capacity, size or type within a device.
- Keep batteries out of the reach of children.
- Keep batteries clean and dry.
- Secondary batteries need to be charged before use.
- Use only the battery in the application for which it was intended.
- When possible, remove the battery from the equipment when not in use.
- Do not store batteries longer than 1 month in discharged state.
- Do not storage batteries longer than 1 year without recharge.
- The battery must be recycled or disposed of properly.

Operating Temperature:		**Storage Temperature:**	
For charge:	0°C to +45°C	< 1 year:	-20°C to +20°C
For discharge:	-20°C to +60°C	< 3 month:	-20°C to +45°C
		< 1 month:	-20°C to +50°C

Recommendation: Store the battery at below 25°C, low humidity, no dust and no corrosive gas atmosphere. Store the battery with a state of charge between 40-60%.

Charging: Charge only with a compliant charger, e.g. RRC-SMB-FPC. Refer also to the manufacturer's instructions or equipment manual for proper charging instructions.

Specifications:

Type	RRC2130
Voltage	7.20V
Capacity	4.17Ah
Max. charge current	2.70A
Max. charge voltage	8.40V
Max. discharge current	6.00A
Dimensions (L x W x H)	151.10mm x 86.60mm x 8.35mm (max.)
Weight	172g

Recycling: Recycle batteries according to national and local regulations. Contact your local representative for assistance. The batteries must be disposed only in a discharged state at the collection center. In case of not fully discharged batteries, provide for a risk against short circuits. Short circuits can be prevented by isolating the terminals with tape.

Declaration of conformity:
CE: The battery complies with the current regulations of the EU guidelines.
FCC: This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Symbols: Explanation of symbols that are on the battery and/or in this manual.

	Caution, consult accompanying documents		Operator's manual; operating instructions
	Mark of conformity to applicable European Directives		Japan, PSE
	United Kingdom, UKCA		Thailand, TISI
	Russia, Gost		Morocco, CMIM
	Canada and USA, UL		UN Transportation Test
	Australia and New Zealand, RCM		Dispose of this product according to local regulations.
	China, CQC		Recycling Symbol
	India, BIS		Taiwan, Recycling Symbol
	Korea, KC		China, RoHS
	Taiwan, BSMI		For Canada & USA: Please call 1-800-822-8837 for information on how to recycle this battery

Talk to our engineers +61 2 9519 1200 · info@mibattery.com.au · mibattery.com.au